

Dante I/O

Dante 8-in 8-out Transmitter Dante 448

Features:

- ▶ Built-in DSP enables signal routing, EQ, limiting, noise gating and programming
- ▶ Integrated with Dante audio network port
- ▶ 4 Analog input and output;
- ▶ 4 Digital input and output for Dante network
- ▶ Support software control and programming through RS-232 port
- ▶ Built-in 8x8 matrix enables seamless mixing and routing for Analog and Digital signals.



SPECIFICATIONS

Dante 448

Input	8 balanced/unbalanced input (XLR)
Input Impedance	Greater than 2000 Ω
Max. Input Level	+4dbu@ 0dB gain
Output	8 balanced/unbalanced output (XLR)
Output Impedance	400 Ω
Max. Output Level	+4dbu balance
Freq. Response	20~20KHz, ± 1 dB
S/N Ratio	Greater than 95dB
THD	Less than 0.05%
Power Requirements	12V DC
Dimensions	44(H) x 178(W) x 220(D) mm