

6-zone Mixer Amplifier with Volume Control



Description:

This series of commercial grade mixer power amplifier deliver clean and powerful sound with reliable performance. Ranging from 70W to 650W RMS power, with built-in 6-zone speaker selector and individual volume controller for each zone. These highly flexible mixer amplifiers designed for a wide variety of voice and background music applications such as restaurants, bars, stores and any small-medium size installations.

Features:

- ▶ With built-in USB/Bluetooth/Tuner/SD card
- ▶ Flexible power rating of 70/130/260/360/500/650W
- ▶ With 3 MIC inputs, 2 AUX inputs and 1 Line output
- ▶ 100V, 70V and 4–16Ohms transformerisolated speaker outputs
- ▶ Independent gain control for each zone
- ▶ Separate BASS and TREBLE control



Steady and powerful performance

SPECIFICATIONS	MZ-200BT	MZ-300BT	MZ-600BT	MZ-1000BT	MZ-2000BT	MZ-3000BT
Rated Power Output	70W	130W	260W	360W	500W	650W
Amplification	Analog 100V Transformer Type					
Output	100V, 70V and 4–16 Ohms					
Frequency Response	60 – 15KHz, +/- 3dB					
THD	Less than 0.5% at 1KHz (1/3 Rated Power)					
S/N Ratio	Better than 85dB					
VOL Range	BASS: 100Hz (± 10dB), TREBLE: 12kHz (±10 dB)					
Controls	Gain controls and power switch					
Cooling	Internal 12VDC fan					
Indicators	Power and Level Indicators					
Power Consumption	110W	190W	365W	510W	720W	910W
Power Requirments	220–240V AC, 50/60 Hz					
Dimensions	89(H) x 483(W) x 366(D) mm					
Built-in Dimensions	2 U rack 19 inch					
Carton Dimensions	185(H) x 520(W) x 435(D) mm					
Net Weight	12 kg	13.5 kg	15 kg	12 kg	13.5 kg	15 kg
Gross Weight	13.8kg	15.2 kg	17 kg	13.8kg	15.2 kg	17 kg
Finish	Panel: aluminium, black Case: steel plate, black					